

The enLux DL1e-xC-120/277V LED Downlight is ideal for commercial retrofit and new construction as well as remodel/retrofit for residential homes.

DL1e-xC-120/277V is a voltage self-declared luminaire; when the incoming power is 120Vac, it will self-declare as a 120Vac driving circuit which results it can be paired with a 120Vac phase cut dimmer, as well as if the incoming is 277Vac, it will self-declare as a 277Vac luminaire and can be paired with a 277Vac phase cut dimmer. **DL1e-xC** has an additional unique feature that the operating power can be adjusted in the field to 10, 8 or 6 watts by setting the dip switch located inside the junction box. It also comes with an optional 0-10V dimming.

enLux Logistic - Ship direct to jobsite















Features:

120/277Vac voltage self-declared & dimmable

10, 8, or 6 Watts, field adjustable

DC Trim - 60 deg beam

TC Trim -100 deg beam

CRI >80

820 - 1100 Lumens @ 10 Watts (depending on CCT & Trim Type)

6 White Tones - 2700K / 3000K / 3500K / 4000K / 4500K / 5000K

IC Rated

4 TC Trim sizes to fit 5", 6", 8" and 9" TC5, TC6, TC8 & TC9 respective

2 DC Trim sizes to fit 6" or 8" ceiling hole. DC6, or DC8 respective

Dry or Damp locations (request sealed lens when placing order)

0-10V dimming (option)

Benefits:

5-Year Warranty 50,000 hour life

Lightweight - Easy to install with patented M Spring

Efficient architecture design

Energy auditing efficient - no need to investigate the line voltage

Flexibility on light output - meeting customer preference at site

ENERGY STAR certified for Commercial and Residential use.















